

CIRCUITOS	TOMADAS(WATTS)					EQUIPAMENTO	POTÊNCIA(W)
	100	200	300	400	ESP.		
1						QDF-1	16.800
2						QDFSE-1	21.100
3						QDFSC-1	12.100
4						QFIL-1	1.680
5						QFAC-1	23.404
6						QF-CFTV	700
7	RESERVA						
8	RESERVA						
9	RESERVA						
<b>SOMA TOTAL</b>							<b>75.784</b>

## GF-1 QUADRO GERAL DE FORÇA - 1

POTÊNCIA(VA)	FATOR POTÊNCIA	TENSÃO(W)	CORRENTE (A)	FASE mm <sup>2</sup>	NEUTRO mm <sup>2</sup>	TERRA mm <sup>2</sup>	DISJUNTOR (A)	DR 25/30mA	CURVA DISJUNTOR
18.261	1	380	28	3x10	10,0	10,0	40	25	C
22.935	1	380	35	3x25	25,0	16,0	70	25	C
13.152	1	380	20	3x6	6,0	6,0	32	25	C
1.826	1	220	8	4,0	4,0	4,0	25	0	C
25.439	1	380	39	3x10	10,0	10,0	40	0	C
761	1	220	3	4,0	4,0	4,0	25	0	C
<b>82.374</b>	<b>0,92</b>	<b>380</b>	<b>125</b>	<b>3x50</b>	<b>50,0</b>	<b>25,0</b>	<b>125</b>		<b>C</b>

**BALANCEAMENTO DE FASES**

<b>A-N</b>	<b>B-N</b>	<b>C-N</b>	<b>ABC</b>
6.522	6.522	5217	
2500	2.609	2609	
4891,304	4.674	3587	
1130	0	696	
9293,478	8073	8.073	
652	0	108,6957	
<b>24.989</b>	<b>21.877</b>	<b>20.290</b>	<b>0</b>